



1850-1865 MHz Cavity Bandpass Filter

Part Number: AB1857B789



ANATECH ELECTRONICS INC
RF & Microwave Filters & Products

Electrical specifications

RX Passband frequency: 1850-1865 MHz
Insertion loss @Passband: 0.7 dB
Return loss @Pasband: 18 dB
Rejection: 75 dB@1930-1945 MHz

Mechanical

Mounting Method: Threaded Mounting Holes
Connector Type: SMA Female
Dimensions: 4.12" x 1.50" x 1.00" in

Environmental

Operating Temperature: -45 to +85° C
Storage Temperature: -55 to +95° C
Shock: 20 G. 11ms
Vibration: 20 G. 5 to 200 MHz

Outline Drawing:

