1801 Morgan Street Rockford, Illinois 61102 800-435-2931 www.molexkits.com



Datasheet for 76650-0056

General Information

Part Number: 76650-0056

Manufacturer: Molex / Waldom

Title: .093" Power Connector Kit

Description: Panel Mount Plug and Receptacle, 12 Circuit

Product Family: Standard .093"

Certificates: (Molex parts within this kit) - EU and China RoHS, UL, CSA and TUV

Country of Origin: Kit assembled in U.S.A.

Specifications

Design

Configuration: Wire to Wire

Pitch: 5.03mm (.198 ")

Connector Type: Plug and Receptacle

Mounting

Orientation: Panel Mount

Circuit Sizes: 12

Current Rating: 5 AmpsVoltage: 600 VoltsWire size: 22-18 AWG

Product Highlights

The Standard .093" is a durable and economical power or signal connector, capable of carrying up to 12 amps per circuit. Tough Nylon housings and robust terminal design create a durable, long lasting product. The Standard .093" products are reliable and offer high value in features and price. These products are an excellent choice for power or signal interconnect applications.

Features and Benefits

- Male and female terminals may be used in either plug or receptacle housings
- Free hanging or panel mount housing version available
- Round terminals may be oriented in any direction for fast assembly

Applications

- Power Supplies
- Appliances
- Gaming Machines
- Vending Machines
- Refrigerators
- · Washing Machines
- Copy Machines



Datasheet for 76650-0056

Bill of Materials for Part No. 76650-0056				
Molex Part No.	Country of Origin	Description	Quantity in Kit	
02-09-1119	USA	.093" Dia. Crimp Female Socket Terminals, 22-18 AWG	14	
02-09-2118	USA	.093" Dia. Crimp Male Pin Terminals, 22-18 AWG	14	
03-09-1121	USA	12-Circuit Panel Mount Nylon Connector Receptacle	1	
03-09-2122	USA	12-Circuit Panel Mount Nylon Connector Plug	1	

Recommended Molex Tool(s) for Part No. 76650-0056*

Molex Part No.	of Origin	Description
63819-1200 *	Sweden	Hand Crimp Tool
11-03-0006 *	Sweden	Extraction Tool
11-02-0003 *	Sweden	Insertion Tool

^{*}Tools not included in kit. Tools ordered separately.