3 METERS LENGTH



Connector A 112522 BNC Jack Straight Bulkhead - Rear Mount Brass Nickel + Heatshrink 50 Ohm RG-178 Continuity/Hi-Pot

Connector B 172313 N-Type Jack Straight Bulkhead - Rear Mount Brass White Bronze + Heatshrink

Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

| | Connector A | | | Cable | | | Connector B | | |
|---|---|---|---|--|--|--|---|--|--|
| | Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: | 112522 BNC BHD JK RG178 RG196 500 BNC Jack Straight Crimp Standard 50 Ohm Bulkhead - Rear Mount Brass Nickel None Phosphor Bronze Gold 4 GHz BNC Jack Straight BHD | | Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length: | RG-178 RG-178 - ST 0.072 ST Braid 0.072 50 Ohm None Continuity Hi-Pot 3 Meters | Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking: | 172313 N-Type BHD JK RG N-Type Jack Straight Solder Standard 50 Ohm Bulkhead - Rear Mo Brass White Bronze None Phosphor Bronze Gold 11 GHz N-Type Jack Straigh 0° | unt | |
| Amphenol CUSTOM CABLE CONTROLLED DOCUMENT DO NOT CODV | | | THIS DRAWING MAY CONTAIN PROPRIETARY INFORMATION FOR ANY PURPOSE DETRIMEN INC. IT MAY NOT BE REPRODU IN ANY FORM WITHOUT THE W CUSTOM CABLE INC. ACCEPTA ESTABLISHES AND AGREEMEN | AND MUST NOT BE U TAL TO CUSTOM CAH CED OR TRANSCRIBH /RITTEN CONSENT O .NCE OF THIS DRAWI | BLE ED F NG Part No: | BNC-ST-JK/N-ST-JK G178 3M | | UNLESS SPECIFIED TOLERANCE: 0-18 inches +/- 1/2" over 18" +/- 2% ASSEMBLY: CENTER LABEL IF LENGTH IS LESS THAN 12 INCHES | |



RoHS 2015/863 Compliance Statement

According to the manufacture of all the component parts contained in this assembly, this product has been determined to be RoHS Compliant with RoHS Directive 2011/65/EU and as amended by Directive 2015/863, and without material exceptions (RoHS3 Complaint).

For the individual component RoHS certificates used in this assembly, please contact Amphenol Custom Cable.

The RoHS Compliance of any product so designated is based upon evidence from the producer (manufacturers') that the component parts comply with the RoHS Directive. Amphenol Custom Cable has taken all reasonable steps to confirm that the OEM (Manufacturer) of the components used in this assembly have provided evidence regarding the absence of the restricted substances to support the manufacturer's claim of compliance.

To the best of our knowledge and with due diligence, we certify that the product listed herein complies with the RoHS requirements.

Date: 10/1/2023

Part Number: Q-0101Z0001003M

Manufacturer: Amphenol Custom Cable

Description: BNC-ST-JK/N-ST-JK G178 3M

This information is valid as of the date indicated for the item (part number) listed.

Director of Quality Assurance

Janice Frank