## **The Bolton Victory**

## Yagi/Panel Cellular Booster





BT459600-YP

## The Victory increases voice, text, and 4G LTE data for homes and offices.

- · Covers up to 4,000 sq. ft.
- · Up to +11 dBi gain outdoor Yagi antenna
- · Best Kit for weaker outside signal
- · Boost 4G LTE signal
- · Simple installation
- · Works with all North American wireless carriers



BOOSTER STUFF					
Uplink (MHz):	698-716	776-787	824-849	1850-1915	1710-1755
Downlink (MHz):	728-746	746-757	869-894	1930-1995	2110-2155
Input/Output Impedance:	$75\Omega$ in $/50\Omega$ out		Power Consumption:		<15W
Maximum Gain:	72 dB		Dimensions:		7.9" x 5" x 1.2"
VSWR:	≤2.0		Weight:		2 lb 3 oz.
Gain Adjustment:	20 dB (Automatic)		AC Power:		Input AC 110V, 60 Hz;
RF Connectors:	F Female (Outside) /				Output DC 5-15V
	N Female (Ir	N Female (Inside)		out Power:	1 Watt EIRP
			Noise Figure: 8	dB	

WHAT'S IN THE BOX				
Bolton Victory Home Booster	BT459600			
Outside Yagi Antenna "Quicksilver 5G" 50 Ohm - N-Female	BT151038			
Inside Panel Antenna "Indoor Board" 50 Ohm - N-Female	BT512501			
Power Supply	BT459792			
50 ft RG6 Cable - White Jacket - F-Male to F-Male (Outdoor)	SC-RG6-50			
20 ft BT240 Cable - White Jacket - N-Male to N-Male (Indoor)	SC-004-20-NN			
Connector: F-Female to N-Male	BT512020			

## **LEGAL STUFF**

Product Specifications may change without prior notice.

FCC ID / IC: RSNF4HOME / 7784A-F4HOME







www.boltontechnical.com



