

		Device Programmers and Development Tools for Microcontrollers																																				
Home	Products	E-Shop	Support	Contact	News	Site Map																																
<p>Quick Links</p> <ul style="list-style-type: none"> Help Desk Downloads All Programmers Device Search Tools Catalogs <p> Shopping Cart Items: 0 Total: \$0.00</p> <p>Your Account</p> <hr/> <p>Products</p> <ul style="list-style-type: none"> Development Tools <ul style="list-style-type: none"> ARM 8051 Other Device programmers <ul style="list-style-type: none"> All Models Universal In-System Gang Adapters Custom made tools OEM tools 		<h2>AE-Q100-A3064</h2> <p>DIP40/ QFP100 specialized adapter for Altera devices.</p>  <p>Description:</p> <p>DIP40/QFP100 specialized adapter for Altera devices. Device package dimensions: body - 14.0 x 14.0 x 1.0 mm, body with pins - 16.0 x 16.0 mm, 0.5 mm pitch.</p> <p>Supported Devices:</p> <p>Click the device programmer model below to get an appropriate list of the devices supported by this programmer with this adapter:</p> <ul style="list-style-type: none"> • ChipProg-48 • ChipProg-G4 <p>Adapter wiring diagram</p> <p>Adapter Connection Table:</p> <table border="1"> <thead> <tr> <th>DIP -40</th> <th>TQFP-100</th> <th>C1, 0.1uF</th> <th>C2, 0.1uF</th> </tr> </thead> <tbody> <tr> <td>11</td> <td>4</td> <td></td> <td></td> </tr> <tr> <td>12</td> <td>15</td> <td></td> <td></td> </tr> <tr> <td>20</td> <td>38,86,11,26,33,43,53,59,65,74,78,95</td> <td>1</td> <td>1</td> </tr> <tr> <td>27</td> <td>62</td> <td></td> <td></td> </tr> <tr> <td>32</td> <td>39,91,3,18,34,51,66,82</td> <td>2</td> <td></td> </tr> <tr> <td>34</td> <td>73</td> <td></td> <td></td> </tr> <tr> <td>39</td> <td>88</td> <td></td> <td>2</td> </tr> </tbody> </table>					DIP -40	TQFP-100	C1, 0.1uF	C2, 0.1uF	11	4			12	15			20	38,86,11,26,33,43,53,59,65,74,78,95	1	1	27	62			32	39,91,3,18,34,51,66,82	2		34	73			39	88		2
DIP -40	TQFP-100	C1, 0.1uF	C2, 0.1uF																																			
11	4																																					
12	15																																					
20	38,86,11,26,33,43,53,59,65,74,78,95	1	1																																			
27	62																																					
32	39,91,3,18,34,51,66,82	2																																				
34	73																																					
39	88		2																																			
Copyright © 2007-2010 Phytion, Inc.		Phone: 718-259-3191 • E-mails: info@phyton.com , sales@phyton.com , support@phyton.com																																				