



155.52 MHz Bandpass Crystal Filter

Part Number: AM155CR151

Center Frequency:	155.52MHz
Bandwidth:	40KHz
Insertion Loss at Center Frequency:	<7dB
Rejection Frequencies:	100KHz- 3GHz
How Many dB:	>60dB
Return Loss:	>10dB
Power Handling:	0 dBm
Dimensions:	2.25 x .60 x .63 inches

Response Plot:

