

# 0936 - 0938 Push Button Switches 0.5A 250Vac

**In house test** 0.5A 250Vac  
**In house test** 0.25A 250Vdc  
 μ contact gap  
 Technical data on pages 4 & 5



**B** BLACK  
**W** WHITE  
**R** RED  
**G** GREEN


**C 0936 P B A**

TERMINAL CODE    FUNCTION CODE    ACTUATOR CODE    ACTUATOR COLOR    BODY CODE

## ORDER FORMAT

TERMINAL CODE	FUNCTION CODE	ACTUATOR CODE	BODY CODE	OPTIONS
C	0936  ON - OFF (momentary ON)	P Small round push 	C Nylon top plate and fixing neck  12.7 Back nut must be fitted	<b>Push button finish</b> Gloss finish only  <b>Push button color</b> Black, white, red, green for other colors call the factory  <b>Cover M327</b> Available for "P" actuator
	0938  ON - OFF (momentary OFF)	K Round push and bezel  Specify Satin chrome or nylon (black / white) bezel	A Metal top plate and fixing neck For Low Voltage (up to 50V) only  12.7 Back nut must be fitted	

### Dimensions (mm) 0936 / 0938 P



### 0936 / 0938 K or M

