



- "X"-Nut™ quarter wave antenna
- EM-M11001-058, NMO Cable Mount
- EMMP-058 Mini-UHF Connector

"X"-Nut™ Antenna Kits

Antenna Kits for Chrome Nut Antenna System Replacement

- Complete Antenna & Cable Kit, includes:
 - "X"-Nut™ quarter wave antenna¹
 - NMO Cable Mount
 - Mini-UHF Connector (supplied loose)
- Stylish high-impact, dual shot Xenoy™/TPV base
- Insert molded brass NMO ring eliminates water intrusion and mating concerns of dissimilar metals
- Dual seal construction for weatherproof protection
- Durable Black Chrome finish for high conductivity and quality appearance
- Delivers up to 10% more operational bandwidth than comparable lower performance Chrome Nut designs

<i>Model</i>	<i>Frequency</i>	<i>Replaces Motorola™ Chrome Nut Kit Part No.</i>
EM-MX5152-MP	152-162 MHz	HAD4008A
EM-MX5162-MP	162-174 MHz	HAD4009A
EM-MX5450-MP	450-520 MHz	HAE4003A
EM-MX5746-MP	746-894 MHz	HAF5002A

<i>Electrical Specifications (Antenna¹)</i>		<i>Mechanical Specifications (Kit¹)</i>	
Impedance	50Ω	Radiator Material	300 Series SS
Gain	0 dBd, (2.0 dBi)	Radiator Plating	Black Chrome
Power Rating	100 W	Base Material	Xenoy™ w/TPV Skirt
Polarization	Linear, Vertical	Connector (supplied loose)	Mini-UHF, Plug
E-Plane	50 Degrees, Nominal	NMO Cable Mount Length	17 ft. (5.1m)
H-Plane	Omnidirectional	Operating Temperature	-40° to 85° C
Ground Plane	Required	Corrosion	Salt and UV Resistant

1. Reference specific "X"-Nut Antenna and NMO Cable Mount part numbers for detailed specifications.

All specifications subject to change without notification.

