## 108 INCHES LENGTH



Connector A 132191 SMA Jack Straight Bulkhead - Rear Mount Brass Gold + Heatshrink 50 Ohm RG-142 Continuity/Hi-Pot Connector B 252123 MCX Plug Right Angle Brass Gold + Heatshrink

## Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

| Right Angle                                       | Connector A   |   |  | Cable  |  |  | Connector B   |   |  |
|---|---|---|--|--|--|--|---|---|--|
| 135° 45°<br>180° 0°<br>225° 270° 315°<br>Eulkhead | Part #:<br>Description:<br>Type:<br>Gender:<br>Body Type:<br>Contact Type:<br>Polarity:<br>Impedance:<br>Mounting:<br>Body Material:<br>Body Finish:<br>IP Rating:<br>Contact Material:<br>Contact Finish:<br>Max. Freq.:<br>Booting: | 132191<br>SMA BHD JK RG55 RG142 RG223 500<br>SMA<br>Jack<br>Straight<br>Solder<br>Standard<br>50 Ohm<br>Bulkhead - Rear Mount<br>Brass<br>Gold<br>None<br>Beryllium Copper<br>Gold<br>12.4 GHz<br>SMA Jack Straight BHD |  | Part #:<br>Description:<br>Dielectric:<br>Shielding:<br>Diameter:<br>Impedance:<br>Sheathing:<br>Testing:<br>Length: | RG-142<br>RG-142 - ST 0.195<br>ST<br>Braid<br>0.195<br>50 Ohm<br>None<br>Continuity Hi-Pot<br>108 Inches | Part #:<br>Description:<br>Type:<br>Gender:<br>Body Type:<br>Contact Type:<br>Polarity:<br>Impedance:<br>Mounting:<br>Body Material:<br>Body Finish:<br>IP Rating:<br>Contact Material:<br>Contact Finish:<br>Max. Freq.:<br>Booting:<br>Clocking: | 252123<br>MCX R/A PLUG RG<br>MCX<br>Plug<br>Right Angle<br>Solder<br>Standard<br>50 Ohm<br>Cable<br>Brass<br>Gold<br>None<br>Brass<br>Gold<br>6 GHz | MCX R/A PLUG RG55 RG142 RG223 500<br>MCX<br>Plug<br>Right Angle<br>Solder<br>Standard<br>50 Ohm<br>Cable<br>Brass<br>Gold<br>None<br>Brass<br>Gold<br>6 GHz<br>MCX Plug Right Angle |  |
| Amphenol  |   |   | THIS DRAWING MAY CONTAIN PATENTED OR<br>PROPRIETARY INFORMATION AND MUST NOT BE USED<br>FOR ANY PURPOSE DETRIMENTAL TO CUSTOM CABLE<br>INC. IT MAY NOT BE REPRODUCED OR TRANSCRIBED<br>IN ANY FORM WITHOUT THE WRITTEN CONSENT OF<br>CUSTOM CABLE INC. ACCEPTANCE OF THIS DRAWING<br>ESTABLISHES AND AGREEMENT OF THE FOREGOING. |  | BLE<br>ED<br>DF<br>ING Part No:  | SMA-ST-JK/MCX-RA-PL G142 108I  |   | UNLESS SPECIFIED<br>TOLERANCE:<br>0-18 inches +/- 1/2"<br>over 18" +/- 2%<br>ASSEMBLY:<br>CENTER LABEL IF LENGTH<br>IS LESS THAN 12 INCHES  |  |



## **RoHS 2015/863 Compliance Statement**

According to the manufacture of all the component parts contained in this assembly, this product has been determined to be RoHS Compliant with RoHS Directive 2011/65/EU and as amended by Directive 2015/863, and without material exceptions (RoHS3 Complaint).

For the individual component RoHS certificates used in this assembly, please contact Amphenol Custom Cable.

The RoHS Compliance of any product so designated is based upon evidence from the producer (manufacturers') that the component parts comply with the RoHS Directive. Amphenol Custom Cable has taken all reasonable steps to confirm that the OEM (Manufacturer) of the components used in this assembly have provided evidence regarding the absence of the restricted substances to support the manufacturer's claim of compliance.

To the best of our knowledge and with due diligence, we certify that the product listed herein complies with the RoHS requirements.

Date: 10/2/2023

Part Number: Q-31019000H108I

Manufacturer: Amphenol Custom Cable

Description: SMA-ST-JK/MCX-RA-PL G142 108I

This information is valid as of the date indicated for the item (part number) listed.

**Director of Quality Assurance** 

Janice Frank