


<b>Phytion™</b>		Device Programmers and Development Tools for Microcontrollers				
Home	Products	E-Shop	Support	Contact	News	Site Map

<p>Quick Links</p> <ul style="list-style-type: none"> <li>Help Desk</li> <li>Downloads</li> <li>All Programmers</li> <li>Device Search</li> <li>Tools Catalogs</li> </ul> <p>Shopping Cart</p> <ul style="list-style-type: none"> <li>Items: 0</li> <li>Total: \$0.00</li> </ul> <p>Your Account</p> <hr/> <p>Products</p> <ul style="list-style-type: none"> <li>Development Tools <ul style="list-style-type: none"> <li>ARM</li> <li>8051</li> <li>Other</li> </ul> </li> <li>Device programmers <ul style="list-style-type: none"> <li>All Models</li> <li>Universal</li> <li>In-System</li> <li>Gang</li> <li>Adapters</li> </ul> </li> <li>Custom made tools</li> <li>OEM tools</li> </ul>	<h2>AE-Q100-XMEGA</h2> <p>DIP40/ QFP100 specialized adapter for Atmel microcontrllers.</p> <div style="display: flex; justify-content: space-around;"> <div style="text-align: center;">  </div> <div style="text-align: left;"> <p><b>Description:</b></p> <p>DIP40/QFP100 specialized adapter for Atmel microcontrllers. Device package dimensions: body - 14.0 x 14.0 x 1.0 mm, body with pins - 16.0 x 16.0 mm, 0.5 mm pitch.</p> <p><b>Supported Devices:</b></p> <p>Click the device programmer model below to get an appropriate list of the devices supported by this programmer with this adapter:</p> <ul style="list-style-type: none"> <li>• <a href="#">ChipProg-48</a></li> <li>• <a href="#">ChipProg-G4</a></li> <li>• <a href="#">ChipProg-40</a></li> </ul> <p><a href="#">Adapter wiring diagram.</a></p> </div> </div> <p><b>Adapter Connection Table:</b></p> <table border="1"> <thead> <tr> <th>Dip40</th> <th>QFP-100</th> </tr> </thead> <tbody> <tr><td>11</td><td>3</td></tr> <tr><td>12</td><td>4</td></tr> <tr><td>7</td><td>13</td></tr> <tr><td>8</td><td>14</td></tr> <tr><td>20</td><td>23</td></tr> <tr><td>19</td><td>24</td></tr> <tr><td>21</td><td>33</td></tr> <tr><td>23</td><td>34</td></tr> <tr><td>27</td><td>43</td></tr> <tr><td>26</td><td>44</td></tr> <tr><td>28</td><td>53</td></tr> <tr><td>30</td><td>54</td></tr> <tr><td>33</td><td>63</td></tr> <tr><td>34</td><td>64</td></tr> <tr><td>35</td><td>73</td></tr> <tr><td>36</td><td>74</td></tr> <tr><td>37</td><td>83</td></tr> <tr><td>38</td><td>84</td></tr> <tr><td>31</td><td>89</td></tr> <tr><td>32</td><td>90</td></tr> <tr><td>14</td><td>93</td></tr> <tr><td>40</td><td>94</td></tr> </tbody> </table>	Dip40	QFP-100	11	3	12	4	7	13	8	14	20	23	19	24	21	33	23	34	27	43	26	44	28	53	30	54	33	63	34	64	35	73	36	74	37	83	38	84	31	89	32	90	14	93	40	94
Dip40	QFP-100																																														
11	3																																														
12	4																																														
7	13																																														
8	14																																														
20	23																																														
19	24																																														
21	33																																														
23	34																																														
27	43																																														
26	44																																														
28	53																																														
30	54																																														
33	63																																														
34	64																																														
35	73																																														
36	74																																														
37	83																																														
38	84																																														
31	89																																														
32	90																																														
14	93																																														
40	94																																														

Copyright © 2007-2010 Phytion, Inc.	Phone: 718-259-3191 • E-mails: <a href="mailto:info@phyton.com">info@phyton.com</a> , <a href="mailto:sales@phyton.com">sales@phyton.com</a> , <a href="mailto:support@phyton.com">support@phyton.com</a>
-------------------------------------	---