TE Internal #: 5222132-1

BNC RF Interface, Jack, 75 Ω , Bayonet, 4 GHz Operating

Frequency, Cable-to-Board, 1 Position, Printed Circuit Board, Panel

Mount

View on TE.com >



Connectors > RF Connectors > Coax Connectors











RF Interface: BNC

RF Connector Style: Jack

RF Connector Mated Outer Diameter (Approximate): 14.53 mm [.572 in]

Impedance: 75Ω

RF Connector Coupling Mechanism: Bayonet

Features

Product Type Features

RF Interface	BNC
RF Connector Style	Jack
Connector System	Cable-to-Board
Sealable	No
Connector & Contact Terminates To	Printed Circuit Board

Configuration Features

PCB Mount Orientation	Vertical
Number of Positions	1
Number of Coaxial Contacts	1

Electrical Characteristics

Impedance	75Ω	
·		

Body Features

Body Material	Die Cast Zinc
Body Plating Material	Nickel



Contact Features

Contact readures	
RF Connector Center Contact Underplating Material	Nickel
	30 μin
RF Connector Center Contact Plating Material	Gold
RF Connector Center Contact Material	Beryllium Copper
Termination Features	
Termination Post & Tail Length	5.33 mm[.21 in]
Termination Method to Printed Circuit Board	Through Hole - Solder

Mechanical Attachment

Panel Attachment Style	Rear Mount
PCB Mount Retention	With
Panel Mount Feature Type	Lockwasher and Nut
RF Connector Coupling Mechanism	Bayonet
Connector Mounting Type	Panel Mount
RF Contact Captivation Method	Mechanical
Detent	With

Dimensions

Mounting Post Length	3.48 mm[.137 in]
Profile Height from PCB	34.93 mm[1.375 in]
RF Connector Mated Outer Diameter (Approximate)	14.53 mm[.572 in]

Usage Conditions

Insulation Option	Uninsulated
Operating Temperature Range	-55 – 85 °C[-67 – 185 °F]

Operation/Application

Packaging Features

Other

Grade	Commercial
Dielectric Material	Polymethylpentene

Product Compliance



For compliance documentation, visit the product page on TE.com>

EU RoHS Directive 2011/65/EU	Compliant with Exemptions
EU ELV Directive 2000/53/EC	Compliant with Exemptions
China RoHS 2 Directive MIIT Order No 32, 2016	Restricted Materials Above Threshold
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JUNE 2023 (235) Candidate List Declared Against: JAN 2021 (211) SVHC > Threshold: Pb (3.7% in Component) Article Safe Usage Statements: Do not eat, drink or smoke when using this product. Wash thoroughly after handling. Recycle if possible and dispose of the article by following all applicable governmental regulations relevant to your geographic location.
Halogen Content	Low Halogen - Br, Cl, F, I < 900 ppm per homogenous material. Also BFR/CFR/PVC Free
Solder Process Capability	Wave solder capable to 265°C

Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulation, the information TE provides on SVHC in articles for this part number is based on the latest European Chemicals Agency (ECHA) 'Guidance on requirements for substances in articles' posted at this URL: https://echa.europa.eu/guidance-documents/guidance-on-reach

Compatible Parts















TE Part # 1-5227079-1
COMM BNC PLUG



TE Part # 228979-7

JACK,COML,SERIES BNC,GOLD PL



TE Part # 413779-3
COML BNC,50 OHM, HEX CRIMP



TE Part # 221221-5

JACK BLKHD 75OHM BNC



TE Part # 228979-6

JACK,COML,SERIES BNC,GOLD PL



TE Part # 414265-3 PLUG, TWIST ON, COML BNC



TE Part # 5413959-3
BNC HEX RT ANG PLUG 50 OHM



TE Part # 1-5221128-0
PLUG,COMMERCIAL BNC



TE Part # 1-5413589-1
KIT PLUG 75 OHM BNC HEX CRIMP



TE Part # 5227079-7 COMM. BNC-PLUG



TE Part # 1-221128-0
PLUG,COMMERCIAL BNC



TE Part # 413589-7 KIT PLUG 75 OHM BNC HEX CRIMP



TE Part # 5221128-1
PLUG,COMMERCIAL BNC



TE Part # 5221185-1
PLUG 75 OHM COML BNC



TE Part # 2-221128-3
PLUG,COMMERCIAL BNC


Customers Also Bought



TE Part #5413194-1 BNC, RT ANG, PCB, JACK



TE Part #4-641126-0 10P MTA100 HDR ASY FL/STR LF



TE Part #321275
TERMINAL,SOLIS FLAG R 4 1/4




TE Part #2170614-1 cage assy, 20 press fit, sfp w















Documents

Product Drawings

JACK, VERTICAL, PCB, 75 OHM, BNC

English

CAD Files

3D PDF

English

Customer View Model

ENG_CVM_5222132-1_A.2d_dxf.zip

English

Customer View Model

ENG_CVM_5222132-1_A.3d_igs.zip

English

Customer View Model

ENG_CVM_5222132-1_A.3d_stp.zip

English

By downloading the CAD file I accept and agree to the **Terms and Conditions** of use.

Datasheets & Catalog Pages

BNC Connectors

English

Product Environmental Compliance

TE Material Declaration

English

Agency Approvals

UL Report

BNC RF Interface, Jack, 75 Ω , Bayonet, 4 GHz Operating Frequency, Cable-to-Board, 1 Position, Printed Circuit Board, Panel Mount



English