
## 18 INCHES LENGTH



Connector A 132119 SMA Jack Straight Bulkhead - Rear Mount Brass Gold + Heatshrink 50 Ohm RG-316 Continuity/Hi-Pot Connector B 112178 BNC Plug Right Angle Brass Nickel + Heatshrink

## Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

Right Angle	Connector A			Cable			Connector B		
90° 135° 180° 225° 270° 270° 0° 0° 0° 0° 0° 0° 0° 0° 0°	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting:	132119 SMA BHD JK RG SMA Jack Straight Solder Standard 50 Ohm Bulkhead - Rear Brass Gold None Beryllium Copper Gold 12.4 GHz SMA Jack Straigh		Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length:	RG-316 RG-316 - ST 0.102 ST Braid 0.102 50 Ohm None Continuity Hi-Pot 18 Inches	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking:	112178 BNC R/A PLUG RG Plug Right Angle Solder Standard 50 Ohm Cable Brass Nickel None Brass Gold 4 GHz BNC Plug Right Ang 0°	174 RG316 LMR100 50O	
Amphenol PROPRIETARY INFORMA   FOR ANY PURPOSE DETE INC. IT MAY NOT BE REP   IN ANY FORM WITHOUT INC. IT MAY NOT BE REP   CONTROLLED DOCUMENT DO NOT CODY			THIS DRAWING MAY CONTAIN PROPRIETARY INFORMATION FOR ANY PURPOSE DETRIMEN INC. IT MAY NOT BE REPRODL IN ANY FORM WITHOUT THE V CUSTOM CABLE INC. ACCEPT ESTABLISHES AND AGREEME?	AND MUST NOT BE U ITAL TO CUSTOM CA JCED OR TRANSCRIB WRITTEN CONSENT O ANCE OF THIS DRAW	BLE ED DF ING Part No:	SMA-ST-JK/BNC-RA-PL G316 18I		UNLESS SPECIFIED TOLERANCE: 0-18 inches +/- 1/2" over 18" +/- 2% ASSEMBLY: CENTER LABEL IF LENGTH IS LESS THAN 12 INCHES	



## **RoHS 2015/863 Compliance Statement**

According to the manufacture of all the component parts contained in this assembly, this product has been determined to be RoHS Compliant with RoHS Directive 2011/65/EU and as amended by Directive 2015/863, and without material exceptions (RoHS3 Complaint).

For the individual component RoHS certificates used in this assembly, please contact Amphenol Custom Cable.

The RoHS Compliance of any product so designated is based upon evidence from the producer (manufacturers') that the component parts comply with the RoHS Directive. Amphenol Custom Cable has taken all reasonable steps to confirm that the OEM (Manufacturer) of the components used in this assembly have provided evidence regarding the absence of the restricted substances to support the manufacturer's claim of compliance.

To the best of our knowledge and with due diligence, we certify that the product listed herein complies with the RoHS requirements.

Date: 10/1/2023

Part Number: Q-2W00D0005018I

Manufacturer: Amphenol Custom Cable

Description: SMA-ST-JK/BNC-RA-PL G316 18I

This information is valid as of the date indicated for the item (part number) listed.

**Director of Quality Assurance** 

Janice Frank