



9.0 GHz Bandpass Filter

Part Number: AE9000B10835

Center Frequency:	9.0 GHz
Passband:	8.5-9.5 GHz
Insertion Loss @ Passband:	<1.5 dB
Return Loss @ Passband:	≥14 dB
Rejection:	>10 dB @ 7.8 GHz >10 dB @ 15 GHz
Power Handling:	30 W
Size:	1.1 x 0.5 x 0.5 inches
Connector Type:	SMA (F)

Outline Drawing:

