sparkfun

Precision Gearmotor - 6 RPM (6-12V)

ROB-12190



images are CC BY-NC-SA 3.0

3D Download: STL, IGES, STEP, Solidworks

Description: These precision gearmotors are incredibly tough and feature full metal gears to help you drive wheels, gears, or almost anything else that needs to turn. They have a gear ratio of 500:1 and operate up to 12 volts and deliver a stall torque of 1111 oz-in. and a max speed of 6 RPM. Each precision gearmotor sports a 6mm diameter D-shaft that protrudes from them.

Features:

· Voltage: 6 - 12 Volts

• Gear Ratio: 500:1

• Stall Torque: 1111 oz-in. (@ 12V)

Speed: 6 RPM (@ 12V)

No Load Current: 80 mA (@ 12V)

Stall Current: 1A (@ 12V)

Insulation Resistance: 20 MOhm

Dielectric Strength: 250VDC

• High Torque Construction

• DC Reversible

• Shaft Size: 6mm Diameter x 0.715" Length

• Weight: 8.05 oz.