
84 INCHES LENGTH



Connector A 112235 BNC Jack Straight Bulkhead - Rear Mount Brass Nickel + Heatshrink 75 Ohm RG-179 Continuity/Hi-Pot Connector B 112179 BNC Plug Right Angle Zinc Nickel + Heatshrink

Assembly & Label Notes

Assembly label to be placed ~ 2" from end of connector A and/ or heat shrink Assembly shall be built with SN96.5 LEAD FREE solder. See Routing Notes for additional assembly & testing instructions.

Right Angle	Connector A			Cable			Connector B		
90° 45° 180° 0° 315° 225° 270° 0° 50° 225° 0° 50° 50°	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Material: Body Finish: IP Rating: Contact Material: Contact Tinish: Max. Freq.: Booting:	112235 BNC BHD JK RG179 750 BNC Jack Straight Crimp Standard 75 Ohm Bulkhead - Rear Mount Brass Nickel None Phosphor Bronze Gold 4 GHz BNC Jack Straight BHD		Part #: Description: Dielectric: Shielding: Diameter: Impedance: Sheathing: Testing: Length:	RG-179 RG-179 - ST 0.1 ST Braid 0.1 75 Ohm None Continuity Hi-Pot 84 Inches	Part #: Description: Type: Gender: Body Type: Contact Type: Polarity: Impedance: Mounting: Body Material: Body Finish: IP Rating: Contact Material: Contact Material: Contact Finish: Max. Freq.: Booting: Clocking:	112179 BNC R/A PLUG RG BNC Plug Right Angle Solder Standard 75 Ohm Cable Zinc Nickel None Brass Gold 4 GHz BNC Plug Right Ang 0°		
Amphenol CUSTOM CABLE CONTROLLED DOCUMENT - DO NOT COPY			THIS DRAWING MAY CONTAIN PATENTED OR PROPRIETARY INFORMATION AND MUST NOT BE USED FOR ANY PURPOSE DETRIMENTAL TO CUSTOM CABLE INC. IT MAY NOT BE REPRODUCED OR TRANSCRIBED IN ANY FORM WITHOUT THE WRITTEN CONSENT OF CUSTOM CABLE INC. ACCEPTANCE OF THIS DRAWING ESTABLISHES AND AGREEMENT OF THE FOREGOING.		BLE ED F ING Part No:	BNC-ST-JK/BNC-RA-PL G179 84I		UNLESS SPECIFIED TOLERANCE: 0-18 inches +/- 1/2" over 18" +/- 2% ASSEMBLY: CENTER LABEL IF LENGTH IS LESS THAN 12 INCHES	



RoHS 2015/863 Compliance Statement

According to the manufacture of all the component parts contained in this assembly, this product has been determined to be RoHS Compliant with RoHS Directive 2011/65/EU and as amended by Directive 2015/863, and without material exceptions (RoHS3 Complaint).

For the individual component RoHS certificates used in this assembly, please contact Amphenol Custom Cable.

The RoHS Compliance of any product so designated is based upon evidence from the producer (manufacturers') that the component parts comply with the RoHS Directive. Amphenol Custom Cable has taken all reasonable steps to confirm that the OEM (Manufacturer) of the components used in this assembly have provided evidence regarding the absence of the restricted substances to support the manufacturer's claim of compliance.

To the best of our knowledge and with due diligence, we certify that the product listed herein complies with the RoHS requirements.

Date: 10/2/2023

Part Number: Q-0600H000S084i

Manufacturer: Amphenol Custom Cable

Description: BNC-ST-JK/BNC-RA-PL G179 84I

This information is valid as of the date indicated for the item (part number) listed.

Director of Quality Assurance

Janice Frank