

3-3/4 Digits 3999 Counts AC/DC Digital Clamp Multimeter

Item: MT-3109

- 3-3/4 digits 3999 counts
- 1% best accuracy
- Auto-range
- Overload protection

Extra function: duty cycle, relative reference, data Hold, sleep mode, auto power off, low battery indication.



Digits	3 3/4 digits 3999 counts
Accuracy	1.0% best accuracy
DCV	400m/4V $\pm(1.0\%+3d)$, 40/400V $\pm(1.0\%+1d)$, 600V $\pm(1.0\%+5d)$
ACV	4/40/400V $\pm(1.2\%+5d)$, 600V $\pm(1.5\%+5d)$
DCA	40A $\pm(2.5\%+5d)$, 400A $\pm(2.5\%+3d)$
ACA	40A $\pm(3.0\%+8d)$, 400A $\pm(3.0\%+5d)$
Resistance	400 Ω $\pm(1.2\%+5d)$, 4k/40k/400k Ω $\pm(1.0\%+5d)$, 4M Ω $\pm(1.2\%+5d)$, 40M Ω $\pm(1.5\%+5d)$
Frequency	10/100/1k/10k/100k/1MHz $\pm(0.1\%+5d)$, 10MHz (For reference only)
Capacitance	40n/400n/4 μ /40 μ F $\pm(5.0\%+10d)$, 100 μ F $\pm(6.0\%+10d)$
Extra function	duty cycle, relative reference, data Hold, sleep mode, auto power off, low battery indication.
Power Source	AAA(1.5V) x 3 pcs (Not included)
Size	8.0 x 2.7 x 1.3 in.
Accessories	Test lead and alligator clips

Order Today! SalesSupport@EclipseTools.com

Eclipse Enterprises, Inc. ● Tel: 804.561.2610 ● Fax: 804.561.2642

13302 Chula Road, Amelia Court House, VA 23002 ● EclipseTools.com