

## 3-1/2 digits 1999 Counts Digital Multimeter with Square Signal

Item: MT-1233D

- Complies with CE safety standard
- 3 1/2 digits 1999 counts
- Palm size for easy storage and carrying
- Square Signal Output
- Built-in stand

Extra functions: backlight, data hold, low battery indication, overload protection indication



Digits	3-1/2 digits 1999 counts
Accuracy	0.5% best accuracy
DCV	200m/2000m/20/200V $\pm(0.8\%+3d)$ , 500V $\pm(1.0\%+3d)$
ACV	200/500V $\pm(1.2\%+5d)$
DCA	2000u/20m/200mA $\pm(1.2\%+5d)$ , 10A $\pm(2.5\%+5d)$
Resistance	200 $\Omega$ $\pm(1.5\%+5d)$ , 2000/20k/200k $\Omega$ $\pm(1.0\%+3d)$ , 20M $\Omega$ $\pm(1.0\%+5d)$ , 200M $\Omega$ $\pm(1.0\%(rdg-10)+10d)$
Square signal output	50Hz (5 Vp-p, 50K $\Omega$ )
Power source	1.5V AAA x 2 (not included)
Size (HXWXD)mm	5.1 x 2.8 x 1.1 in.
Individual packing	Double blister
Accessories	Test leads

**Order Today! [SalesSupport@EclipseTools.com](mailto:SalesSupport@EclipseTools.com)**

Eclipse Enterprises, Inc. ● Tel: 804.561.2610 ● Fax: 804.561.2642

13302 Chula Road, Amelia Court House, VA 23002 ● [EclipseTools.com](http://EclipseTools.com)